

**SOCKET
&SEE™**

VVD PRO
Vibrating Non Contact
AC Voltage Detector



- Visual indication of volts present given by flashing red LED
- Physical indication of volts present given by vibration
- Balanced sensitivity for more accurate detection
- Operating voltage range 50 - 1000 VAC
- Robust and ergonomic construction
- Handy pocket size with clip
- Bright LED flashlight
- Lightweight
- Safety standard BS EN 61010
- Suitable for CAT IV use

Description

The Socket & See VVD PRO provides both visual (red flashing LED) and physical (vibration) indication that a voltage between 50 - 1000V AC is present. This makes the VVD PRO ideal for use in noisy or poorly lit areas.

Light weight, compact and robust, the VVD PRO is designed to fit easily in the users pocket or tool bag making it convenient to always have on site. It also features a bright LED flashlight.

Suitable for CAT IV use

Specification

Operating Voltage Range	50 - 1000 VAC
Operating Frequency Range	50 - 60 Hz
Temperature Range	-10°C to 50°C
Humidity	80% max
Safety standard	BSEN 61010
Batteries	2 x AAA
Dimensions	150xx x 26mm x 20mm
Weight (no batteries)	28 g

Century Road,
High Carr Business Park,
Newcastle-Under-Lyme,
ST5 7UG
United Kingdom

www.socketandsee.co.uk
info@socketandsee.co.uk
Tel: 44 (0)1782 567096
Fax: 44 (0)1782 567095
Socket & See is a brand name of UK Test Instruments Limited

go test..

SAS051v1